

Lingua CHC


Lingua Digital Infrared Charging Case



Description

The Lingua Charging Case can charge up to 64 Lingua infrared receivers at once. In just 4 hours, all receivers are fully charged.

The case has been designed for frequent use and safe transportation. It is built from durable, rugged materials and has several handles. As a result, it is easy and comfortable to move around. Cases may also easily be stacked on top of one another. Finally, the top lid has room to store cables.



The Lingua Charging Case also comes with a smart web server. With an easy to use visual representation of the charging case, all information about the receivers is

available at a glance. The web server displays: charging percentages, fully charged status, indication of possible error states, and it allows you to easily update the receivers to the latest firmware.

Features

- » Room for 64 receivers (includes status LED)
- » Rapid charging
- » Sturdy case for safe transport
- » Onboard web server
- » Possibility to cascade Lingua CHC (via network and power)
- » Easy updates of Lingua CHC and Lingua Receivers
- » Factory reset button
- » Lingua CHC status LED

Connectivity

- » Factory reset button
- » Lingua CHC status LED
- » 2 Ethernet connections
- » 2 Mains connection (for cascading)
- » 64 receivers

Certification

Region	Certification
Europe	CE

Specifications

Mechanical	
Material	Steel
Color	RAL 9011
Size (mm)	515 (w) × 275 (h) × 405 (d)
Size packed (mm)	575 (w) × 295 (h) × 425 (d)
Weight (Empty)	12,500
Weight (Full: 64 receivers)	20,000
Weight Packed (Empty)	13,500
Electrical	
Mains voltage	~125/230V (50-60Hz)
Max. Power consumption	300 W
Power Consumption without Receivers	50 W
Fuse	T2AL / 250V
Environmental	
Operating temperature	0 – 45°C
Storage and transport temperature	-20 – 70°C
Humidity	<95%, >5%